


Model: K3

1.Introduction



2.Specification

1. Accuracy: ± 0.2 degrees (34~45°C, place it in the operating environment for 30 minutes before use)
2. Abnormal automatic alarm: flashing + "Di Di" sound
3. Automatic measurement: measuring distance 5cm ~ 10cm
4. Screen: Digital display
5. Charging method:USB charging or battery(18650 Li-ion).
6. Install method: nail hook, double-sided adhesive sticking, bracket fixing
7. Environment temperature: 10°C~40°C (Recommended 15°C~35°C)
8. Infrared measuring range: 0~50°C
9. Response time: 0.5s
10. Input: DC 5V
11. Weight: 350g
12. Dimensions: 170*115*140mm
13. Standby: About one week
14. Counting capacity: 999

3.Status Description

1. Standby: The red dot in the bottom of the display lights up in turn. (Fig. 1)
2. Insufficient power: The horizontal bar lights up in the middle of the display. (Fig. 2)
3. Normal temperature: Flashing green lights and alarm 'Di'. (Fig. 3)



Fig. 1



Fig. 2



Fig. 3

4. Abnormal temperature: Flashing red lights and alarm 'Di Di'.(Fig. 4)

5. Default (bod:object mode) :

- 'Lo': Ultra-low temperature alarm. (Fig.5)
- 'Hi' : Ultra-high temperature alarm.(Fig. 6)



Fig. 4



Fig. 5



Fig. 6

4.Operation Instruction

1. Temperature measurement: Front of the thermometer and approach it within 5-10 cm. (Fig. 7)





Fig. 7

2. Mode switching: There is a small hole on the back of the device (Fig. 8). You can use a 3mm diameter screwdriver to insert the hole and then press the button.

(1) Temperature unit: Press 'mode switch hole' then select 'C' or 'F' (Fig.9, 10) C: Celsius F: Fahrenheit



Fig. 8



Fig. 9



Fig. 10

- (2) Mode: Long press mode switch hole for 3 seconds to switch the temperature measurement mode (Sur: surface mode, bod: object mode, Cou: counting mode)



Fig. 11





Fig. 12




Fig. 13

3.Install and replace battery


- (1) Remove three screws
- (2) Open the back base and install 18650 Li battery




4.Install method



1.Nail hook



2.Bracket fixing



3.Double-sided adhesive sticking

